LIGHTWAY 3 - RECESSED WITH TRIM

Product Installation guide

IP20

For Indoor use only

DON'T TOUCH THE LED !

25°C

RECOMMENDED ROOM TEMPERATURE

MAKE SURE THE POWER IS OFF DURING INSTALLATION

220-240V~
50/60 Hz

RISK OF FIRE AND ELECTRICAL SHOCK

INSTALLATION INSTRUCTIONS

Please read all instructions before beginning installation:

1. Turn off electrical power before starting the installation of the light fixture.

2. The feeding voltage must not exceed the specified fixture voltage.

3. This product must be installed by an eligible electrician.

4. Make sure the luminaire is mounted to a secure structure. Mounting the fixture in inappropriate way could lead to serious injury.
5. This luminaire is class 1, it must be earthed in a reliable way.

6. The light source of this luminaire shall only be replaced by the manufacturer, his service agent or a similar qualified person.

7. Wear gloves and safety glasses at all times when removing the luminaire from carton,installing, servicing or performing maintenance

8. Do not install damaged product! This luminaire is properly packed to avoid being damaged during transit. Inspect to confirm before installation. Any damaged or broken part during or after assembly should be replaced.

9. Unauthorized repairs or modifications will void warranty.

DISCLAIMER

Section View:

Dimensions in mm

Applicable optics:

1.CutOff Washer

2.Opal & Prismatic

projects@vicelighting.com - **www.vicelighting.com**

Lebanon 11-0125 - Beirut +961 1 585000 - **France** 7502 Paris + 33 06 75 32 73 23

LIGHTWAY 3 - RECESSED WITH TRIM

Product Installation guide

Preparing the area

1
- Cut the Ceiling in a rectangular shape respecting the Cut-Out Dimensions(L x 38 mm).
- Make sure to have access to the cable.

2 Join the LED connectors together.

3
- Open the driver Box.
- Connect the mains cable to the terminal block.
- Re-close the Box and put it in the right place.

4 Hold Back the spring and lift the luminaire to install it in the ceiling

5 Make sure the luminaire is well fixed.

VICE

projects@vicelighting.com - **www.vicelighting.com**

Lebanon 11-0125 - Beirut +961 1 585000 - **France** 7502 Paris + 33 06 75 32 73 23

LIGHTWAY 3 - RECESSED WITH TRIM

Product Installation guide

Annexe A

*Code Example:
L3 I RW -- -- -- --- - -- -- - I 120 **I** (Individual)
L3 I RW -- -- -- --- - -- -- - I 120 **B** (Beginning)
L3 I RW -- -- -- --- - -- -- - I 120 **M** (Middle)
L3 I RW -- -- -- --- - -- -- - I 120 **E** (End)

Opal/Prismatic

Length Code*	L (mm) (Two End Caps)	L1 (mm) (One End Cap)	L2 (mm) (No End Cap)
60	610	602	594
70	708	700	692
80	806	798	790
90	904	896	888
100	1002	994	986
110	1100	1092	1084
120	1198	1190	1182
130	1296	1288	1280
140	1394	1386	1378
150	1492	1484	1476
160	1590	1582	1574
170	1688	1680	1672
180	1786	1778	1770
190	1884	1876	1868
200	1982	1974	1966
210	2080	2072	2064
220	2178	2170	2162
230	2276	2268	2260
240	2374	2366	2358
250	2472	2464	2456
260	2570	2562	2554
270	2668	2660	2652
280	2766	2758	2750
290	2864	2856	2848
300	2962	2954	2946

*Code Example: L3 I RW AO -- -- --- - -- -- - I **120** -

CutOff Washer

Length Code*	L (mm) (Two End Caps)	L1 (mm) (One End Cap)	L2 (mm) (No End Cap)
60	611	603	595
70	709	701	693
80	807	799	791
90	905	897	889
100	1003	995	987
110	1101	1093	1085
120	1199	1191	1183
130	1297	1289	1281
140	1395	1387	1379
150	1493	1485	1477
160	1591	1583	1575
170	1689	1681	1673
180	1787	1779	1771
190	1885	1877	1869
200	1983	1975	1967
210	2081	2073	2065
220	2179	2171	2163
230	2277	2269	2261
240	2375	2367	2359
250	2473	2465	2457
260	2571	2563	2555
270	2669	2661	2653
280	2767	2759	2751
290	2865	2857	2849
300	2963	2955	2947

*Code Example: L3 I RW WO -- -- --- - -- -- - I **120** -

Annexe B

Asymmetrical optics:

Below section views shows the light direction and the power feeding location for the asymmetrical optic.

Light Direction